

CHAT® 170 | CHATAttach® 170

Personal/Group Speakerphone compatible with Skype for Business

Speakerphones for individual, small, medium or large group use, the CHAT 170 and CHATAttach 170 connect to PCs and laptops for rich, full-duplex audio communication. The CHAT 170 and CHATAttach 170 are the perfect solution for Skype for Business users whether in the office or conference room for greatly enhanced collaboration.



DELIVERS SUPERIOR
HANDS-FREE AUDIO
COMPATIBLE WITH
SKYPE FOR BUSINESS
SERVER 2010

APPLICATIONS

Skype for Business

Perfect for:

- + Boardrooms
- + Small, medium or large Conference Rooms
- + Executive Offices
- + Home Offices
- + Ad-hoc conferences any time, any place

ADVANTAGES

Provides high quality speakerphone capabilities on PCs or laptops:

- + Connect the CHAT 170 or the CHATAttach 170 to PCs and laptops via USB for hands-free, full-duplex audio with Skype for Business
- + Incoming calls ring on the CHAT 170 and the CHATAttach 170
- + True plug-and-play operation
 - > Requires no drivers or software to be installed
- + Also provides crystal-clear audio for video conferencing and streamed multimedia content
- + Eliminates the need for large, expensive tabletop conference phones in executive offices
- + Replaces the PC's speakers and microphone with a high-quality, hands-free audio solution
- + Sleek industrial design complements the professional environment of boardrooms and executive offices

Enjoy crisp, clear audio:

- + Advanced ClearOne audio processing technologies deliver remarkably rich, full audio for natural, effortless conversations:
 - > True full-duplex performance allows users to listen and speak at the same time without audio cutting in and out
 - > Distributed Echo Cancellation® eliminates acoustic echo
 - > Noise cancellation identifies and removes ambient room noise
 - > Advanced automatic level management automatically adjusts microphone levels
- + Three built-in microphones provide full 360-degree coverage up to 8 feet from device
 - > Easily manage 1-6 call participants
 - > Provides rich audio from the far side participants
- + Full bandwidth frequency response delivers better audio

> **CHAT 170 COMPONENTS**



CHAT 170 Unit
Part # 910-156-250



USB 2.0 Connection Cable
Part # 830-156-200



Quick Start Guide
Part # 800-156-253

> **CHATAttach 170 COMPONENTS**

CHATAttach Packout for the CHAT 170



Two CHAT 170 Units
Part # 910-156-250



USB 2.0 Connection Cable
Part # 830-156-200



CHATAttach Cable
Part # 830-156-010L



CHATAttach Power Supply
Part # 551-156-200



CHATAttach Quick Start Guide
Part # 800-156-225

Ready to use out of the box

All the components you need to quickly get up and running, including cabling and Quick Start Guide.

CHATAttach Expansion Cable Packout



CHATAttach Cable
Part # 830-156-010L




CHATAttach Power Supply
Part # 551-156-200




CHATAttach Quick Start Guide
Part # 800-156-225

> **ROOM APPLICATIONS**

CHAT 170



CHATAttach 170



Configuration Software

Allows users to easily switch between devices; software applies optimized settings to CHAT 170 for each device. Auto-updates from the Web to keep software & CHAT 170 up-to-date with the latest enhancements.

> **SPECIFICATIONS**

System Requirements

Windows XP, Vista, 7 or 8/8.1

Connections

USB:

Version 2.0 Compatible
Type: Mini-B Female

Keyed Connector:

Keyed RJ-45 (8-conductor)

Controls

Volume Up
Volume Down
Microphone Mute

Audio

Speaker:

Bandwidth: 190 Hz - 20 kHz

Max Output Level:

85 dB SPL @ 1 foot (0.30 meter)

Microphone

Bandwidth: 50 Hz - 7.75 kHz

Environmental

Operating Temperature:

41 - 104° F (5 - 40° C)

Processing

Full Duplex
Distributed Echo Cancellation (D.E.C.)®
Noise Cancellation (NC)
Automatic Level Control (ALC)
First Mic Priority

Power

USB:

5 VDC @ 500 mA Maximum

External:

Input: 100 - 240 VAC
Output: 9 VDC @ 560 mA

Tip: Power
Ring: Ground

Mechanical

Dimensions (W x D x H):
7.4" x 7.4" x 1.8" (18.8 cm x 18.8 cm x 4.6 cm)

Weight:
1.17 lbs (0.53 kg)

Compliance

RoHS
REACH
FCC Class A Part 15
ICES-003
CE Listed
UL Listed

Model Numbers

910-156-250 CHAT 170

- Single CHAT 170 and Connecting Cable

910-156-250-00 CHATAttach 170

- Two (2) CHAT 170 Devices, Connecting Cables and Power Supply

Accessory Part Numbers

910-156-225 CHATAttach Expansion Kit

- Includes Cables, Power Supply and Quick Start Guide to Update Two (2) CHAT 170 Devices to CHATAttach

> **CLEARONE LOCATIONS**

HEADQUARTERS:

Salt Lake City, UT USA

5225 Wiley Post Way
Suite 500
Salt Lake City, UT 84116

Tel: 801-975-7200

Toll Free: 800-945-7730

Fax: 801-977-0087

E-mail: sales@clearone.com

Latin America

Tel: 801-974-3621

E-mail: global@clearone.com

EMEA

Tel: 44 (0) 1189 036 053

E-mail: global@clearone.com

APAC

Tel: 801-303-3388

E-mail: global@clearone.com

TechSales

Tel: 800.705.2103

techsales@clearone.com

Technical Support

Tel: 800.283.5936

E-mail: tech.support@clearone.com